Doepke



DATA SHEET

residual current circuit-breaker DFS 2 016-2/0,03-AC V24 sensitive to residual currents Type AC, Rated voltage 24 V Article number 09114608



Function

Residual current circuit-breakers (RCCBs) are components for implementing protective measure "Automatic disconnection of the power supply" as per VDE 0100 part 410 or corresponding international installation regulations. Series DFS 2 devices are compact two-pole residual current circuit-breakers for single-phase networks. In the standard design, they only take up two module-width units of space. In spite of the compact dimensions, a number of different tripping currents and characteristics are available at rated currents, depending on the design, up to 125 A. They also have large two-tier terminals for large conductor cross-sections, a practical multi-functional switch toggle and can be provided with labels using free-of-charge software. Switches with residual current characteristic AC only detect AC residual currents. They cannot detect pulsating DC residual currents so are not permitted for use as residual current operated protective devices in Germany. They are therefore only available as export models. Devices in design V are made for special voltages.

Mounting

quick fastening to mounting rail, any installation position, supply from any direction

Notes

Other special voltages available upon request

Accessories

automatic reclosing devices DFA, terminal caps KA, information stickers HAS, auxiliary switches DHi, restart locks DFS WES, software DBS

Technical Data

Technical Data	DFS 2 016-2/0,03-AC V24
Series	DFS 2 AC V
Number of poles	2
Residual current type	AC
Rated current (AC)	16 A
Rated residual current IAn	0.03 A
Short-time delayed	false
Selective	false
min. Operating voltage range of test circuit	20 V
max. Operating voltage range of test circuit	34 V
Maximum disconnection times	$1 \cdot \Delta n \le 300 \text{ ms}; 5 \cdot \Delta n \le 40 \text{ ms}$
	load circuit
Specification	load disconnect contact
min. Contact opening	4 mm
Rated voltage (AC)	24 V
Rated current (AC)	16 A
Rated short-circuit current	10 kA
Surge current strength	0.25 kA


Doepke

The experts in residual current protection technology

Technical Data	DFS 2 016-2/0,03-AC V24
max. Total rated switching	500 A
capacity	
Rated insulation voltage	400 V
Rated impulse withstand voltage	4 KV
Rated frequency	50 Hz
Current heat loss per current path	0.18 W
Thermal Backup-fuse OCPD	16 A
Short-circuit backup-fuse SCPD	100 A
Back-up fuse type	gG
	screw-type terminal top and bottom (load circuit)
Neutral conductor position	left or right
Protection against direct contact	DGUV V3, VDE 0660-514, finger and back-of-hand proof
Connection C1 Maximum number of conductors per terminal	2 (conductors of same type and cross-section)
Cross section solid	1-wire: 1.5 mm ² 50 mm ² ; 2-wire: 1.5 mm ² 16 mm ²
Connecting capacity flexible	1-wire: 1.5 mm ² 50 mm ² ; 2-wire: 1.5 mm ² 16 mm ²
Cross section stranded	1-wire: 1.5 mm ² 50 mm ² ; 2-wire: 1.5 mm ² 16 mm ²
Cross section AWG, solid	151
Cross section AWG, stranded	151
Cross section AWG, flexible	151
Cross section AWG, flexible with errule	15 1
Fightening torque	2.5 Nm 3 Nm
	General data
Operating position	optional
nax. Operating altitude above MSL	2000 M
Mechanical endurance	min. 5000 cycles
Electrical endurance	min. 2000 cycles
Surrounding atmosphere	normal environmental conditions
Storage temperature	-35 °C 75 °C
Ambient temperature	-25 °C 40 °C
Climate resistance	according to IEC 60068-2-30: humid heat / cyclic (25 °C / 55 °C; 93 % / 97 % RH)
Shock resistance	20 g / 20 ms Duration
atigue limit	> 5 g (f ≤ 80 Hz, duration > 30 min.)
Housing type	distribution board housing
nstallation type	Mounting rail (35 mm)
Housing material	thermoplastic
Protection class	IP20 (installed: IP40)
sealable	true
Width	36 mm
Height	85 mm
Depth	
nstallation depth	69 mm
Module widths	2
Weight	 0.26 kg
Design requirements/Standards	VDE 0664-10, DIN EN 61008-1
Degree of pollution	


Doepke

Dimensions



Dimensional drawing Group view

Wiring example



Wiring diagram