


DATA SHEET

Article number: 09117598

residual current circuit-breaker DFS 2 016-2/0,50-B SK

AC/DC sensitive type B





Function

Residual current circuit-breakers (RCCBs) are components for implementing protective measure "Automatic disconnection of the power supply" as per IEC 60364-4-41 or corresponding national installation regulations. Series DFS 2 devices are compact two-pole residual current circuit-breakers for single-phase networks. In the standard design, they only take up two module-width units of space. In spite of the compact dimensions, a number of different tripping currents and characteristics are available at rated currents, depending on the design, up to 125 A. They also have large two-tier terminals for large conductor cross-sections, a practical multi-functional switch toggle and can be provided with labels using free-of-charge software. Type B residual current circuit-breakers detect smooth DC residual currents and all other residual currents at frequencies up to 150,000 Hz. The operating voltage required for this is taken from the mains supply. Correct power supply is ensured when the voltage between the mains conductors is \geq 50 V. Pulsating and AC residual currents are detected independent of the mains voltage. For residual current circuit-breakers with characteristic curve SK, the frequency response of the tripping current is designed so that residual currents with high frequencies, such as in the clock frequency range for frequency converters, as opposed to the rated frequency are detected with significantly reduced sensitivity. Undesired trips caused by leakage currents can therefore be widely avoided. However, fire protection depending on the rated residual current of the switch (0.03 A, 0.1 A or 0.3 A) is only provided for residual currents with frequencies up to 1 kHz, 300 Hz or 100 Hz, while the devices with tripping current frequency response B+ or NK offer protection over the entire tripping frequency range up to 20 kHz or 150 kHz, respectively. Devices in the standard design are intended for monitoring circuits with a rated voltage of 230 V and a rated frequency of 50 Hz.

Features

High level of immunity against leakage and residual currents due to operational conditions from frequency 1 kHz and higher, AC/DC sensitive for residual currents with frequencies and mixed frequencies of o Hz (smooth direct current) up to 150 kHz, high availability even of voltage-independent detection of smooth DC residual current and AC residual current with frequencies not equal to 50/60 Hz thanks to full functional compatibility with mains voltages from at least 50 V AC on any two active conductors, mains-voltage-independent tripping when type A residual currents occur, compact design for all rated currents, high short-circuit resistance, double-sided two-tier terminals for large conductor cross-section and busbar, switch position indicator, viewing window for labels, multifunction switch toggle with three positions: "on", "off" and "tripped", Neutral conductor position left or right

Mounting

quick fastening to mounting rail, any installation position, supply preferably from above

Applications

Commercial and industrial installations with TT, TN-S and TN-C-S systems, where power electronics equipment is used without galvanic isolation from the mains, e.g. frequency converters, switching power supplies, high-frequency converters, photovoltaic installations and UPS equipment with frequency converters without transformers.

Notes

suitable for use in 50 Hz AC networks, RCCBs for other frequencies available upon request, Not designed for use in direct current networks or on the output side of controlled electrical equipment such as frequency converters.

Accessories

automatic reclosing devices DFA, terminal caps KA, information stickers HAS, auxiliary switches DHi, restart locks DFS WES, software DBS

Technical data

Series	DFS 2 B SK
Number of poles	2
Residual current type	В
Tripping characteristic curve	SK
Rated current (AC)	16 A
Rated residual current I∆n	0.5 A


Technical changes reserved 2025_11_29 doepke_09117598_dbl_en.pdf 1/3

se ; V o V
, v
AC
-
AC
ms
150 kHz
.5 · IΔn: ≤ 40 ms
0.8 W
ircuit
ect contact
nm
) V
A
kA
A.
) A
) V
·V
Hz
W
A
A
G .
A ² s
:A
and bottom (load circuit)
right
ger and back-of-hand proof
ype and cross-section)
a using a smooth of the control of t
2-wire: 1.5 mm ² 16 mm ²
2-wire: 1.5 mm ² 16 mm ²
2-wire: 1.5 mm ² 16 mm ²
1
1
1
1
3 Nm
ıl data
onal
o m
o cycles
o cycles
ental conditions
70 °C
. 40 °C
at / cyclic (25 °C / 55 °C; 93 % / 97 % RH)
s Duration
uration > 30 min.)
oard housing
ail (35 mm)
plastic
lled: IP40)
Je .
nm
nm
nm
nm
9 kg
RM E 8601, DIN EN 61008-1, EN 62423
r

3/3


Certifications

Dimensions




Dimensioned drawing residual current circuit-breaker DFS 2 016-2/0,50-B SK

Wiring example



Wiring example residual current circuit-breaker DFS 2 016-2/0,50-B SK

Diagrams



Diagrams residual current circuit-breaker DFS 2 016-2/0,50-B SK

Technical changes reserved 2025_11_29 doepke_09117598_dbl_en.pdf