Doepke



DATA SHEET

residual current circuit-breaker

DFS 2 100-2/0,10-A KV



sensitive to pulsating and alternating currents Type A, increased surgecurrent resistant, short-time delayed, lightning resistant Article number 09165609

10000 🖂 🕸 🗠 KV G

Function

Residual current circuit-breakers (RCCBs) are components for implementing protective measure "Automatic disconnection of the power supply" as per VDE 0100 part 410 or corresponding international installation regulations. Series DFS 2 devices are compact two-pole residual current circuit-breakers for single-phase networks. In the standard design, they only take up two module-width units of space. In spite of the compact dimensions, a number of different tripping currents and characteristics are available at rated currents, depending on the design, up to 125 A. They also have large two-tier terminals for large conductor cross-sections, a practical multi-functional switch toggle and can be provided with labels using free-of-charge software. Type A residual current circuit-breakers are sensitive to pulsating and alternating currents. This function is independent of the mains voltage. Because they feature a response delay, residual current circuit-breakers, they are significantly less sensitive to brief impulse-like residual currents and facilitate problem-free operation, even when lightning or switching overvoltage in the system causes capacitative surge residual currents or insulation flashovers with a secondary current up to the zero point of the mains voltage. They therefore meet the requirements for lightning-resistant RCCBs as per Austrian standard ÖVE E 8601. The tripping times set out in national and international design regulations for instantaneous RCCBs are also observed by the KV design devices. In principle, therefore, they may be used instead of a standard breaker. Devices in the standard design are intended for monitoring circuits with a rated voltage of 230 V and a rated frequency of 50 Hz.

Features

high immunity against surge currents and mains-voltage-operated secondary current impulses, tripping not dependent on mains and auxiliary voltage, sensitive to AC residual currents and pulsating DC residual currents (type A), compact design for all rated currents, high short-circuit resistance, double-sided two-tier terminals for large conductor cross-section and busbar, switch position indicator, viewing window for labels, multifunction switch toggle with three positions: "on", "off" and "tripped", Neutral conductor position left or right

Mounting

quick fastening to mounting rail, any installation position, supply from any direction

Applications

Power supplies to residential and purpose-built building as well as industrial facilities with TN-S, TT and TN-C-S networks, in which conventional RCCBs trip following transient leakage currents and this is not desired, such as in systems with long cable lengths behind the RCCB, lighting systems with lots of fluorescent lamps (> 20 lamps), computer systems and solar power systems, Excluded is the application in TN-C systems and for the protection of installations in which electronic equipment could generate smooth DC currents or residual currents with frequencies other than 50 Hz. Comprehensive protection is not provided in this case. For these applications we recommend our AC/DC sensitive residual current circuit-breakers (Type B or B+).

Accessories

automatic reclosing devices DFA, terminal caps KA, information stickers HAS, auxiliary switches DHi, restart locks DFS WES, software DBS

Technical Data

Technical Data	DFS 2 100-2/0,10-A KV
Series	DFS 2 A KV
Number of poles	2
Residual current type	A
Rated current (AC)	100 A
Rated residual current IΔn	0.1 A
Short-time delayed	true

Doepke

The experts in residual current protection technology

Technical Data	DFS 2 100-2/0,10-A KV
Selective	false
nin. Operating voltage range of est circuit	100 V
max. Operating voltage range of est circuit	250 V
Non-trip time	10 MS
	load circuit
Specification	load disconnect contact
nin. Contact opening	4 mm
Rated voltage (AC)	230 V
Rated current (AC)	100 A
Rated short-circuit current	10 kA
Surge current strength	3 kA
nax. Total rated switching apacity	1000 A
Rated insulation voltage	400 V
Rated impulse withstand voltage	4 kV
Rated frequency	50 Hz
Current heat loss per current bath	6 W
Thermal Backup-fuse OCPD	80 A
Short-circuit backup-fuse SCPD	125 A
Back-up fuse type	gG
	screw-type terminal top and bottom (load circuit)
Neutral conductor position	left or right
Protection against direct contact	DGUV V3, VDE 0660-514, finger and back-of-hand proof
Connection C1 Maximum number of conductors per rerminal	2 (conductors of same type and cross-section)
Cross section solid	1-wire: 1.5 mm ² 50 mm ² ; 2-wire: 1.5 mm ² 16 mm ²
Connecting capacity flexible	1-wire: 1.5 mm ² 50 mm ² ; 2-wire: 1.5 mm ² 16 mm ²
Cross section stranded	1-wire: 1.5 mm ² 50 mm ² ; 2-wire: 1.5 mm ² 16 mm ²
Cross section AWG, solid	15 1
Cross section AWG, stranded	15 1
Cross section AWG, flexible	15 1
Cross section AWG, flexible with errule	15 1
Fightening torque	2.5 Nm 3 Nm
	General data
Operating position	optional
nax. Operating altitude above MSL	2000 M
Aechanical endurance	min. 5000 cycles
lectrical endurance	min. 2000 cycles
Surrounding atmosphere	normal environmental conditions
torage temperature	-35 °C 75 °C
Ambient temperature	-25 °C 40 °C
Climate resistance	according to IEC 60068-2-30: humid heat / cyclic (25 °C / 55 °C; 93 % / 97 % RH)
bhock resistance	20 g / 20 ms Duration
Fatigue limit	> 5 g (f ≤ 80 Hz, duration > 30 min.)
Housing type	distribution board housing
nstallation type	Mounting rail (35 mm)


Doepke

The experts in residual current protection technology

Technical Data	DFS 2 100-2/0,10-A KV
Housing material	thermoplastic
Protection class	IP20 (installed: IP40)
sealable	true
Width	36 mm
Height	85 mm
Depth	75 mm
Installation depth	69 mm
Module widths	2
Weight	0.25 kg
Design requirements/Standards	VDE 0664-10, DIN EN 61008-1, ÖVE/ÖNORM E 8601
Degree of pollution	2
Certifications	VDE

Dimensions

Wiring example



Dimensional drawing Group view

Wiring diagram