

# DATA SHEET Article number : 09916559

# miniature circuit-breakers DLS 6i Ko6-1

for industrial facilities, K characteristics, 10 kA



## 10000 🕸

#### **Function**

The task of miniature circuit breakers is to automatically disconnect circuits in order to protect lines and connected devices. After disconnection, they can be manually reactivated without the fuse sets having to be replaced, for example. Each of our miniature circuit breakers is equipped with a trip-free mechanism, which guarantees safe deactivation even if, for example, a switching knob is mechanically blocked. A key requirement in DIN VDE 0100 is to protect cables, lines and installation devices from overload and shortcircuit. This can be achieved using miniature circuit-breaker (MCBs). In industrial installations and also in commercial buildings, they often take on additional protection of equipment and devices where there are usually stricter requirements than when used in residential buildings. Miniature circuit-breakers utilise both the magnetic and heat effect of the electrical current. If the current jumps to a value that is too high when a short-circuit occurs, the MCB interrupts the circuit using the magnetic field of an energised coil. The heat that develops when there is continuous overload causes the bimetal to warp, which trips the breaker. The DLS 6 family of miniature circuitbreakers, characterised by a large selection of different types for broad application fields, are available for residential and purpose-built facilities, as well as for industrial applications. The compact design provides lots of space for wiring and large clamping area, as well as the option of using conventional wiring rails for easy processing. The variants also have a large, folding label window and a clearly labelled display for the operating status. A number of additional devices such as operating current trip, and auxiliary/fault sensor switches, render possible general-purpose use of the miniature circuit-breakers. Its high rated switching capacity of 10 kA means the DLS 6i variant is particularly suited to usage in industrial systems for example. Also, the large selection of rated currents and tripping characteristics enable the miniature circuit-breaker to be used in a diverse range of applications. Switches with characteristic K are optimised for fuse-protecting power circuits (motor and transformer load circuits) with high switch-on currents.

#### **Features**

rated switching capacity 10 kA, screw terminals with strain-relief clamps with wide terminal cross-section range for rail and line wiring on both connection sides, quick fastening for removal of multiple miniature circuit-breakers from the bottom or top interconnection, large, folding label window for a secure hold and protection of the label, use of conventional wiring rails, ON/OFF switch position indicator on the switch toggle, accessories retro-fittable on the right, labelling software free of charge

#### Mounting

quick fastening to mounting rail, any installation position

### **Applications**

suitable for use in power supplies for industrial facilities and purpose-built buildings or buildings for commercial use

#### **Accessories**

terminal caps KA, software DBS, restart locks DEASS, auxiliary switches DHi, trip-indicating auxiliary contact DHi-S, operating current trip DASA, documentation

#### Technical data


Series	DLS 6i
Number of poles	1
Tripping characteristic	K
Supply side	left or right
Adjustment range of overload tripping	1.05 1.2
Adjustment range of short-circuit tripping	8 12
Tripping factor over frequency band	1.5 at DC; 1.1 at 100 Hz; 1.2 at 200 Hz; 1.3 at 300 Hz; 1.4 at 400 Hz
Test current factor tripping electromagnetic	12
Test current multiplier, trip, thermal	1.2
Test current factor retaining electromagnetic	8
Test current factor retaining thermal	1.05
Reference temperature thermal release	20 ℃
Isolation class	C at 250 V AC; B at 400 V AC

Technical changes reserved 2025\_11\_29 doepke\_09916559\_dbl\_en.pdf 1/3

load circuit
230 V, 400 V 60 V 60 V 6 A 6 A 10 kA 2 kV 4 kV 50 Hz (16.67 Hz 60 Hz) 1.8 W 125 A gL, gG Safety fuse as per DIN EN 0636 Ill screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
60 V 6 A 6 A 10 kA 2 kV 4 kV 50 Hz (16.67 Hz 60 Hz) 1.8 W 125 A gL, gG Safety fuse as per DIN EN 0636 Ill screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
6 A 6 A 10 kA 2 kV 4 kV 50 Hz (16.67 Hz 60 Hz) 1.8 W 125 A gL, gG Safety fuse as per DIN EN 0636 III screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
6 A  10 kA  2 kV  4 kV  50 Hz (16.67 Hz 60 Hz)  1.8 W  125 A  gL, gG  Safety fuse as per DIN EN 0636  III  screw terminals with strain-relief clamp top (load circuit)  DGUV V2, VDE 0660-514, finger and back-of-hand proof
10 kA 2 kV 4 kV 50 Hz (16.67 Hz 60 Hz) 1.8 W 125 A gL, gG Safety fuse as per DIN EN 0636 III screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
2 kV 4 kV 50 Hz (16.67 Hz 60 Hz) 1.8 W 125 A gL, gG Safety fuse as per DIN EN 0636 III screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
4 kV 50 Hz (16.67 Hz 60 Hz) 1.8 W 125 A gL, gG Safety fuse as per DIN EN 0636 III screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
50 Hz (16.67 Hz 60 Hz)  1.8 W  125 A  gL, gG  Safety fuse as per DIN EN 0636  III  screw terminals with strain-relief clamp top (load circuit)  DGUV V2, VDE 0660-514, finger and back-of-hand proof
1.8 W  125 A  gL, gG  Safety fuse as per DIN EN 0636  III  screw terminals with strain-relief clamp top (load circuit)  DGUV V2, VDE 0660-514, finger and back-of-hand proof
1.8 W  125 A  gL, gG  Safety fuse as per DIN EN 0636  III  screw terminals with strain-relief clamp top (load circuit)  DGUV V2, VDE 0660-514, finger and back-of-hand proof
gL, gG Safety fuse as per DIN EN 0636 III screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
gL, gG Safety fuse as per DIN EN 0636 III screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
Safety fuse as per DIN EN 0636 III screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
III screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
screw terminals with strain-relief clamp top (load circuit) DGUV V2, VDE 0660-514, finger and back-of-hand proof
DGUV V2, VDE 0660-514, finger and back-of-hand proof
- · · · · · · · · · · · · · · · · · · ·
copper conductor
• •
2 (conductors of same type and cross-section)
1-wire: 0.5 mm <sup>2</sup> 25 mm <sup>2</sup>
1-wire: 1 mm <sup>2</sup> 16 mm <sup>2</sup>
o.5 mm² 16 mm²
1-wire: 1.5 mm <sup>2</sup> 25 mm <sup>2</sup>
max. 2.5 Nm
max. 3 mm
2 mm
2 111111
ar mm²
25 mm²
anno de maior de milaborator de la forma de atama de adordita
screw terminals with strain-relief clamp bottom (load circuit)
DGUV V2, VDE 0660-514, finger and back-of-hand proof
2 (conductors of same type and cross-section)
1-wire: 0.5 mm² 35 mm²
1-wire: 1 mm <sup>2</sup> 25 mm <sup>2</sup>
0.5 mm <sup>2</sup> 16 mm <sup>2</sup>
1-wire: 1.5 mm² 35 mm²
max. 2.5 Nm
2 mm
35 mm²
33
may 2 mm
max. 3 mm General data
optional
min. 20000 switching cycles
-40 °C 70 °C
-25 °C 70 °C
damp/heat: constant as per DIN EN 60068-2-78, cyclical as per DIN EN 60068-2-30
25 g / 11 ms Duration
> 15 g acc. to DIN EN 60068-2-59 during a load with I1
distribution board housing
Mounting rail (35 mm)
thermoplastic
IP20
true
17.7 mm
82.5 mm
74 mm
68 mm
1
0.12 kg
IEC 60947-2, DIN EN 60947-2, VDE 0660-101

Degree of pollution

# **Dimensions**




Dimensioned drawing miniature circuit-breakers DLS 6i Ko6-1

# Wiring example



Wiring example miniature circuit-breakers DLS 6i Ko6-1

### Diagrams



Diagrams miniature circuit-breakers DLS 6i Ko6-1

2