


DATA SHEET

Article number: 09948327



AC/DC sensitive type B+, fire protection according to VDE 0100-420







Function

RCCB/MCB combinations (RCBO) are residual current operated circuit-breakers with integral overcurrent protection for protecting systems in the event of a short-circuit and overload as per the requirements of VDE 0100 Part 430, and for protecting persons, farm animals and material items in the event of earth leakage currents as per VDE 0100 Part 410. Overload tripping occurs at currents in the overload range through a short-time delayed, heat-sensitive bimetal trip and at short-circuit currents through an electromagnetic instantaneous trip. The DRCBO 4 have a rated switching capacity of 6 kA. They provide a labelling area in addition to the tripping indicator. Type B+ residual current circuit-breakers detect smooth DC residual currents and all other residual currents at frequencies up to 20,000 Hz. The operating voltage required for this is taken from the mains supply. Correct power supply is ensured when the voltage between the mains conductors is ≥ 50 V. Pulsating and AC residual currents are detected independent of the mains voltage. RCBOs with tripping characteristic C are primarily suitable for power circuits with high switch-on or peak currents, as their short-circuit trip value is five to ten times the rated current. Devices in standard design are intended for monitoring circuits with a rated voltage of 230 V or 400 V and a rated frequency of 50 Hz.

AC/DC sensitive for residual currents with frequencies of o Hz (smooth direct current) up to 20,000 Hz, mains-voltage-independent tripping when type A residual currents occur, compact design for all rated currents, switch position indicator, separate indication of tripping cause, strain-relief clamps with a wide terminal cross-section range on both connection sides, neutral conductor right, labelling

Mounting

quick fastening to mounting rail, any installation position, supply preferably from above

Applications

commercial and industrial installations with TT, TN-S and TN-C-S systems, where power electronics equipment is used without galvanic isolation from the mains, e.q. frequency converters, switching power supplies, high-frequency converters, photovoltaic installations and UPS equipment with frequency converters without transformers, Type B+ and type B RCBOs with characteristic curve NK should be used where fire protection is legally required.

suitable for use in 50 Hz AC networks, RCBOs are also available for other frequencies upon request, not designed for use in direct current networks or on the output side of controlled electrical equipment such as frequency converters

auxiliary switches DRCBO 4 Hi 2, wiring components DRCBO 4-busbars 4-pole


Technical data

| Series | DRCBO 4 |
|--|---------|
| Number of poles | 3+N |
| Residual current type | B+ |
| Rated current (AC) | 32 A |
| Rated residual current I∆n | o.o3 A |
| Short-time delayed | true |
| Selective | false |
| min. Operating voltage range of test circuit | 170 V |
| max. Operating voltage range of test circuit | 250 V |
| Minimum rated operating voltage (Type A/AC | o V AC |
| operation) | |

Technical changes reserved 2025_11_29 doepke_09948327_dbl_en.pdf 1/3

| Minimum rated operating voltage (Type B | 50 V AC |
|---|---|
| operation) | 30 + 110 |
| Non-trip time | 10 MS |
| Tripping frequency | 0 Hz 20 kHz |
| Maximum disconnection times | 1 · IΔn: ≤ 300 ms; 5 · IΔn: ≤ 40 ms |
| Tripping characteristic | C C |
| Supply side | Up |
| Operating voltage (AC) | max. 440 V |
| Internal consumption | max. 1.3 W |
| internal consomption | load circuit |
| Specification | load disconnect contact |
| Rated voltage (AC) | 230 V, 400 V |
| Rated current (AC) | 32 A |
| Rated short-circuit current | 6 kA |
| Surge current strength | 3 kA |
| max. Total rated switching capacity | 6 kA |
| Rated insulation voltage | 440 V |
| | · · |
| Rated impulse withstand voltage | 4 kV |
| Rated frequency | 50 Hz |
| Current heat loss per current path | 5.1 W |
| Back-up fuse type | gG |
| Overvoltage class | |
| M. Luland data and Co. | screw-type terminal top, bottom (load circuit) |
| Neutral conductor position | right |
| Connection C1 Maximum number of | 2 (conductors of same type and cross-section) |
| conductors per terminal | |
| Cross section solid | 1-wire: 1 mm ² 35 mm ² ; 2-wire: 1 mm ² 10 mm ² |
| Connecting capacity flexible | 1-wire: 1 mm ² 25 mm ² ; 2-wire: 1 mm ² 10 mm ² |
| Cross section stranded | 1-wire: 1 mm ² 25 mm ² ; 2-wire: 1 mm ² 10 mm ² |
| Tightening torque | 2 Nm 2.4 Nm |
| | General data |
| Operating position | optional |
| Mechanical endurance | min. 5000 switching cycles |
| Electrical endurance | min. 2000 switching cycles |
| Storage temperature | -40 °C 70 °C |
| Ambient temperature | -25 °C 40 °C |
| Climate resistance | according to IEC 60068-2-30 |
| Shock resistance | 20 g / 20 ms Duration |
| Fatigue limit | > 5 g (f ≤ 80 Hz, duration > 30 min.) |
| Housing type | distribution board housing |
| Installation type | Mounting rail (35 mm) |
| Housing material | thermoplastic |
| Protection class | IP20 (installed: IP40) |
| Width | 8o mm |
| Height | 91 mm |
| Depth | 73.5 mm |
| Installation depth | 67 mm |
| Module widths | 4.5 |
| Weight | 0.556 kg |
| Design requirements/Standards | VDE 0664-20, VDE 0664-40, VDE 0664-401, |
| | EN 61009-1, EN 62423, ÖVE/ÖNORM E 8601 |
| Power limitation category | 3 |
| Degree of pollution | 2 |
| Certifications | VDE |
| | |


Dimensions



 $Dimensioned\ drawing\ residual\ current\ operated\ circuit-breakers\ with\ integral\ overcurrent\ protection\ DRCBO\ 4\ C_{32}/o, o_3/3N-B+1/o, o_3/3N-B+1$


Technical changes reserved 2025_11_29 doepke_09948327_dbl_en.pdf 2/3

Wiring example



 $Wiring example \ residual \ current \ operated \ circuit-breakers \ with \ integral \ overcurrent \ protection \ DRCBO \ 4 \ C_{32}/o, o_3/3N-B+1/o, o_3/3$

Diagrams



Diagrams residual current operated circuit-breakers with integral overcurrent protection DRCBO 4 C_{32}/o , $o_3/3N-B+$