

DATA SHEET

fuse plug sets
DSE Do2-35 MI
for load disconnector Tytan
Article number 09980127



symbolic image

Function

Fuse plug sets can be used as accessories for initial or replacement equipping of fuse-switch-disconnectors. #The fuse plug sets of this series are suitable for Tytan II fuse-switch-disconnectors. Your box can be easily installed on the mounting rail and thus be used as a reserve box.#Fuse plug sets of this series are accessories to Tytan II fuse-switch-disconnectors and consist of three plugs, three fitting cartridges and three fuses of the respective variant. The box has a rear bracket for snapping on a mounting rail, which enables it to be used as spare box in a distribution board.# This series of fuse plug sets contains fuses with mechanical display.

Features

Tytan Do empty housing fitting, reserve box, 3 fuses, 3 fitted cartridges, 3 plugs, one 63 A colour-coded

Mounting

Storage case, quick fastening to mounting rail

Applications

The components are suitable for use in power supplies to residential and purpose-built buildings as well as industrial facilities.


Notes

DLS 8 are approved as listed UL devices (UL-listed). When they are used, the authorisation conditions must be observed in accordance with UL 508, Function of the supplementary protectors: overload protection, disconnection, switching, A corresponding back-up fuse is used for short-circuit protection.

Technical Data

Technical Data	DSE D02-35 MI
Series	DSE D02-35 MI
Utilization category	gL/gG characteristics
Colour code	black
Socket type can be used	D02
Operating voltage (AC)	230 V, 400 V
	Display fuse failure
Туре	little flag
	load circuit
Rated current (AC)	35 A
	General data
Housing type	distribution board housing
Installation type	Mounting rail (35 mm)
Width	54 mm
Height	45 mm
Depth	74 mm
Design requirements/Standards	EN 60715, EN 50022, VDE 0110, VDE 0638, EN 60947

Dimensions



Dimensional drawing Group view