



DATA SHEET
fuse plug sets
DSE Do2-35 MI
for load disconnecter Tytan
Article number 09980127



[Internetlink](#)

symbolic image

Function

Fuse plug sets can be used as accessories for initial or replacement equipping of fuse-switch-disconnectors. Fuse plug sets of this series are accessories to Tytan II fuse-switch-disconnectors and consist of three plugs, three fitting cartridges and three fuses of the respective variant. The box has a rear bracket for snapping on a mounting rail, which allows for using it as spare box in a distribution board. This series of fuse plug sets contains fuses with mechanical display.

Features

Tytan Do empty housing fitting, reserve box, 3 fuses, 3 fitted cartridges, 3 plugs, one 63 A colour-coded

Mounting

Storage case: quick fastening to mounting rail


Applications

The components are suitable for use in power supplies to residential and purpose-built buildings as well as industrial facilities.

Technical Data

Technical Data	DSE Do2-35 MI
Series	DSE Do2-35 MI
suitable for	Coron 2/Tytan
Operating voltage (AC)	230 V, 400 V
Type	Display fuse failure little flag load circuit
Rated voltage (AC)	400 V
Housing type	D02 (fuse mounting) General data distribution board housing
Mounting type	Mounting rail (35 mm)
Width	54 mm
Height	45 mm
Depth	74 mm
Design requirements/Standards	EN 60715, EN 50022, VDE 0110, VDE 0638, EN 60947

Dimensions



Dimensional drawing Group view

