



[Internetlink](#)


DATA SHEET

restart locks

Tytan II Do WES-K-gn

in designs with plastic and cylinder lock

Article number 09980137



Function

This equipment prevents the unintentional activation of switching devices, e.g. during maintenance work. For implementing protective measure #93secure against restart" during maintenance and repair work. The lock can be used to reliably prevent the mains voltage from being inadvertently switched on with the Tytan fused circuit-breaker by an authorised person, for example. The lock is supplied in a storage case that can be easily fixed to a mounting rail.

Features

cylinder lock design includes two keys, supplied in practical storage case for mounting on mounting rails

Mounting

quick fastening to mounting rail


Applications

use in power supplies to residential and purpose-built buildings as well as industrial facilities in conjunction with Tytan Do main fuse switch-disconnectors

Technical Data

Technical Data	Tytan II Do WES-K-gn
Series	Plastic lock
suitable for	Tytan
Accessories design	restart lock
	General data
Housing type	distribution board housing
Mounting type	Mounting rail (35 mm)
Width	54 mm
Height	45 mm
Depth	74 mm
Width (modules)	3
Design requirements/Standards	EN 60715, EN 50022, VDE 0110, VDE 0638, EN 60947

Dimensions



Dimensional drawing Group view