

DATA SHEET

Article number : 09980682

fuse plug sets
DSE Do-16

for load disconnector Tytan



1/2

Function

Fuse plug sets can be used as accessories for initial or replacement equipping of fuse-switch-disconnectors. #The fuse plug sets of this series are suitable for Tytan II fuse-switch-disconnectors. Your box can be easily installed on the mounting rail and thus be used as a reserve box.#Fuse plug sets of this series are accessories to Tytan II fuse-switch-disconnectors and consist of three plugs, three fitting cartridges and three fuses of the respective variant. The box has a rear bracket for snapping on a mounting rail, which enables it to be used as spare box in a distribution board.# This series of fuse plug sets includes fuses with LED displays, which will start flashing if a fuse is blown.

Features

Tytan Do empty housing fitting, reserve box, 3 fuses, 3 fitted cartridges, 3 plugs, one 63 A colour-coded

Mounting

Storage case, quick fastening to mounting rail


Applications

The components are suitable for use in power supplies to residential and purpose-built buildings as well as industrial facilities.

Technical data

Series	DSE Do-16
Utilization category	gL/gG characteristics
Colour code	grey
Socket type can be used	D01
Operating voltage (AC)	50 V 400 V
Operating voltage (DC)	50 V 110 V
	Display (fuse failure)
Туре	LED
	load circuit
Rated current (AC)	16 A
	General data
Storage temperature	-40 °C 70 °C
Housing type	distribution board housing
Installation type	Mounting rail (35 mm)
Width	54 mm
Height	45 mm
Depth	74 mm
Weight	0.119 kg
Design requirements/Standards	EN 60715, EN 50022, VDE 0110, VDE 0638, EN 60947

Dimensions



Dimensioned drawing fuse plug sets DSE Do-16

Technical changes reserved 2025_10_14 doepke_09980682_dbl_en.pdf



2025_10_14 Technical changes reserved doepke_o998o682_dbl_en.pdf 2/2