



DATA SHEET
fuse plug sets
DSE Do-40
for load disconnecter Tytan
 Article number 09980687



Function

Fuse plug sets can be used as accessories for initial or replacement equipping of fuse-switch-disconnectors. #The fuse plug sets of this series are suitable for Tytan II fuse-switch-disconnectors. Your box can be easily installed on the mounting rail and thus be used as a reserve box. #Fuse plug sets of this series are accessories to Tytan II fuse-switch-disconnectors and consist of three plugs, three fitting cartridges and three fuses of the respective variant. The box has a rear bracket for snapping on a mounting rail, which enables it to be used as spare box in a distribution board. # This series of fuse plug sets includes fuses with LED displays, which will start flashing if a fuse is blown.

Features

Tytan Do empty housing fitting, reserve box, 3 fuses, 3 fitted cartridges, 3 plugs, one 63 A colour-coded

Mounting

Storage case, quick fastening to mounting rail

Applications


The components are suitable for use in power supplies to residential and purpose-built buildings as well as industrial facilities.

Technical Data

| Technical Data | DSE Do-40 |
|-------------------------------|--|
| Series | DSE Do-40 |
| Utilization category | gL/gG characteristics |
| Colour code | green |
| Socket type can be used | D02 |
| Operating voltage (AC) | 50 V ... 400 V |
| Operating voltage (DC) | 50 V ... 110 V |
| | Display (fuse failure) |
| Type | LED |
| | load circuit |
| Rated current (AC) | 40 A |
| | General data |
| Housing type | distribution board housing |
| Installation type | Mounting rail (35 mm) |
| Width | 54 mm |
| Height | 45 mm |
| Depth | 74 mm |
| Weight | 0.136 kg |
| Design requirements/Standards | EN 60715, EN 50022, VDE 0110, VDE 0638, EN 60947 |

Subject to technical changes

Dimensions



Dimensional drawing Group view