

## TECHNISCHE INFORMATION

### TECHNICAL INFORMATION

#### Verlustleistung DFS 2/4 30 mA-1000 mA

Power dissipation per pole DFS 2/4 30 mA-1000 mA

Nennstrom Rated current A	Leistung Power dissipation W	
	DFS 2	DFS 4
16	0,18	0,2
25	0,45	0,5
40	1,1	1,3
63	2,8	3,1
80	4,0	5,0
100	6,0	7,5
125	10	11,2

#### Verlustleistung DFS 2/4 10 mA

Power dissipation per pole DFS 2/4 10 mA

Nennstrom Rated current A	Leistung Power dissipation W	
	DFS 2	DFS 4
16	1,2	1,4
25	3,0	3,2
40	7,5	–