

DATA SHEET Article number : 09980034

doorbell transformers RK 12 S

short-circuit-proof thanks to PTC



Function

Bell transformers generate one or more output voltages for the operation of doorbell systems, such as bells, buzzers or gongs. Transformers for converting mains voltage of 230 V to functional extra-low voltage (FELV).

Features

short-circuit-proof thanks to PTC, certified as per EN 61558, certified by VDE, with ENEC approval mark for use in all Europe

Mounting

quick fastening to mounting rail, any installation position

Applications

Bell transformers in series RK are used for the AC power supply to bell systems, lock systems and relay circuits, for example.

Notes

Restore operation after a short-circuit by briefly disconnecting the primary power input, With small loads, or idling, the output voltage may rise, Only for transient loading, In the case of permanent loads we recommend using safety transformers.

Accessories


mounting kits RK

Technical data

Series	RK 12 S
Operating voltage (AC)	230 V
Operating frequency	50 Hz
Internal consumption	max. 12 W
	load circuit
Rated voltage	8 V/2 A (AC), 12 V/1.5 A (AC)
Rated voltage (AC)	8 V, 12 V
Rated current (AC)	2 A, 1.5 A
Rated power	max. 18 VA
Rated frequency	50 Hz
Type overload protection thermal	PTC, primary side
·	screw terminals with strain-relief clamp top and bottom
Connection C1 Maximum number of	2
conductors per terminal	
Cross section solid	1-wire: 1.5 mm ² 4 mm ² ; 2-wire: 1.5 mm ² 2.5 mm ²
	General data
Duty cycle	short-time operation (Duty cycle ≤ 1 min bei
	Nennlast, 5 min at max. 20 % of the nominal load)
Operating position	optional
Storage temperature	-40 °C 70 °C
Housing type	distribution board housing, wall-mounted housing
Installation type	Mounting rail (35 mm), Wall mounting
Housing material	polycarbonate (PC)
Protection class	IP20
Width	36 mm
Height	90 mm
Depth	65 mm
Installation depth	60 mm


Module widths	2
Weight	o.398 kg
Design requirements/Standards	EN 61558-1

Dimensions



Dimensioned drawing doorbell transformers RK 12 ${\sf S}$

Wiring example



Wiring example doorbell transformers RK 12 S