



[Internetlink](#)

## DATA SHEET

restart locks

**DEASS**

for miniature circuit-breakers in DLS 6 series

Article number 09917983



### Function

This equipment prevents the unintentional activation of switching devices, e.g. during maintenance work. The DEASS on/off interlock prevents miniature circuit-breakers from series DLS 6 from being switched on or off. On the one hand, the DEASS can be used to implement protective measure "secure against restart" during maintenance and repair work, and on the other, it protects sensitive circuits from being switched off inadvertently, such as in IT systems, UPS installations and alarm systems. The interlock can be sealed or secured using a conventional padlock (shackle diameter up to 6 mm). The protective function of the miniature circuit-breaker is not affected by the use of the DEASS due to its trip-free mechanism.

### Features

quick and universal use, sealable, lockable with a conventional padlock

### Mounting

Mounting directly on the toggle of the switching devices


### Applications

For general protection from switching on or off power supplies to residential and purpose-built buildings as well as industrial facilities.

### Technical Data

Technical Data	DEASS
Series	DEASS
suitable for	DLS 6
Accessories design	restart lock
	General data
Mounting type	Device extension
Housing material	ABS
Specification housing cover	coloured
sealable	true
Width	16.6 mm
Height	30.2 mm
Depth	12.4 mm

### Dimensions



Dimensional drawing Group view

STEP file

