TECHNICAL INFORMATION

DRCA 1 set – the first steps



⚠ Please do not connect the device yet!

- If you already have a version of the DRCA 1 on your computer, please uninstall this before carrying out the new installation.
 You can do this by navigating to <Start><Settings><Control Panel><Programs and Features><Uninstall or change a program>
 <Uninstall DRCA 1>. Removing National Instruments components: Navigate to <C:\Programs (x86)\National Instruments\Shared\NIUninstaller> (standard path) to find the file <uninst.exe>. Start this file and highlight all the components listed there.
 To do this, select the first component and press <Shift+End> to highlight everything. Select <Delete>.
 You will need to restart your computer after uninstalling.
- 2. Connect the installation USB stick to your computer.

 Once the program Setup_DRCA1_V2_en.exe has been executed, the installation will start.
- 3. You will be prompted to select a directory for DRCA 1 and for the National Instruments files, and to accept the licence agreements of Doepke Schaltgeräte GmbH and National Instruments (this software was created using NI LabVIEW).
- 4. A total of approx. 55 components will be installed on your computer unless it already has components from other LabVIEW applications. Installation may take up to 20 minutes.
- **5.** Once installation is complete, you will be prompted to restart your computer.
- **6.** Restart the computer, then connect the device to a free USB port on your computer.
- 7. You will be prompted to install drivers for the device select 'Search/install automatically'.

 You do not need to activate the option 'Connect to the Internet'. The hardware is now installed automatically.
- 8. Start the analysis software by navigating to **<Start><All Programs><Doepke Schaltgeraete><DRCA 1>** or by double-clicking on the symbol on the desktop.

Scope of delivery

<u>'</u>	
1 × installation USB stick	DRCA 1 V2-SW
1 × measuring unit	DRCA1
1 × connection cable	DRCA 1-MC
1 × current transformer	DRCA 1-CT 070
1 × USB cable	
1 × manual/documentation	